

120 Vac Input

838-13616
AUDIO POWER AMP 2CH

[Extra] [GD ROM DRIVE]


5k pot

400-5397
SW REGU FOR JVS


INPUT AC 90~110V
OUTPUT +3.3V12A, +5V10A, +12V2A

56p EDGE CONNECTOR JAMMA (P=3.96mm)

- 0 1 GND
- 0 2 GND
- 0 3 GND
- 0 4 +5V
- 0 5 +5V
- 0 6 +5V
- 0 7 (+5V)
- 0 8 (-5V)
- 0 9 (-5V)
- 0 10 +12V
- 0 11 +12V
- 0 12 (KEY)
- 0 13 (KEY)
- 0 14 COIN METER 1
- 0 15 (COIN METER 2)
- 0 16 9 (COIN LOCKOUT 1)
- 0 17 K (COIN LOCKOUT 2)
- 0 18 L (SPEAKER (+))
- 0 19 L (SPEAKER (-))
- 0 20 (N.C.)
- 0 21 M (N.C.)
- 0 22 RED
- 0 23 N GREEN
- 0 24 BLUE
- 0 25 P SYNC
- 0 26 14 GND (SYNC)
- 0 27 OR TEST
- 0 28 S SERVICE (TILT)
- 0 29 16 COIN1
- 0 30 T COIN2
- 0 31 17 1P START
- 0 32 U 2P START
- 0 33 18 (1P UP)
- 0 34 V (2P UP)
- 0 35 19 (1P DOWN)
- 0 36 W (2P DOWN)
- 0 37 20 (1P LEFT)
- 0 38 X (2P LEFT)
- 0 39 21 (1P RIGHT)
- 0 40 Y (2P RIGHT)
- 0 41 22 1P SW1
- 0 42 Z 2P SW1
- 0 43 23 1P SW2
- 0 44 a 2P SW2
- 0 45 24 1P SW3
- 0 46 b 2P SW3
- 0 47 25 (1P SW4)
- 0 48 c 2P SW4
- 0 49 26 (1P SW5)
- 0 50 d 2P SW5
- 0 51 27 GND
- 0 52 e GND
- 0 53 28 GND
- 0 54 f GND



CODE	COLOR	CODE	COLOR	CODE	COLOR
10	RED	60	ORANGE	C	BROWN
20	BLUE	70	BLACK	D	PURPLE
30	YELLOW	80	GRAY	E	LIGHT GREEN
40	GREEN	A	PINK		
50	WHITE	B	SKY BLUE		



The character following the wire color code indicates the size of the wire.
 K — AWG18 UL1015
 L — AWG20 UL1007
 None — AWG22 UL1007

JAMMA CONNECTIONS USED ARE:
 ∞ VIDEO OUT
 ∞ SWITCH INPUTS
 ∞ SWITCH GROUND RETURNS
 ∞ COIN COUNTER OUTPUT

NOTE: THERE ARE TO BE NO CONNECTIONS MADE TO THE JAMMA INTERFACE OTHER THAN THE ABOVE FOREMENTIONED.

Triforce KIT UNIVERSAL
 WIRING DIAGRAM (1/1)